

METHODS FOR SIGNALING BROADCAST AND MULTICAST INFORMATION IN COMMUNICATION NETWORKS

BACKGROUND OF THE INVENTION

Field of the Invention

[0001] The present invention relates to signaling information in communication systems or networks supporting Broadcast-Multicast services (BCMCS).

Related Art

[0002] Current second generation and third generation wireless systems are primarily designed to support unicast voice and data services. The support of these unicast services to the end user has been achieved through various advances in wireless and networking technologies. The current emphasis in international standardization bodies such as 3GPP and 3GPP2 is on the design of protocols and procedures that allow the support of Broadcast-Multicast Services (BCMCS) over evolving networks. BCMCS is a bandwidth-conserving technology that reduces traffic by simultaneously delivering a single stream of information to a large number of recipients. Examples of these services include voice dispatch or Press-To-Talk (PTT) type services, broadcast/multicast streaming, etc.

[0003] There has been recent industry interest in the Public Safety Wireless Network (PSWN) context, where support of BCMCS may be especially important in terms of radio resource management. Radio resource management procedures may be needed to achieve low delay in establishment and delivery of BCMCS content, to provide scalability in terms of the number of multicast groups and/or number of users per multicast group, and to provide advanced service capabilities (e.g., ability to monitor/extract content from multiple BCMCS streams). Further, radio resource management procedures may be needed to achieve high spectral efficiency, to provide security (authentication, encryption and identity protection), and to improve mobile station battery life. Thus, radio resource management procedures that improve spectral efficiency, battery life and/or provide service flexibility are of interest to network operators.

[0004] Thus, new technical challenges are emerging in the design of radio resource management procedures to improve spectral efficiency and service flexibility in third generation wireless communication systems providing mixed voice and data services. In meeting mixed voice and data service demands, system overhead information should be carried for signaling BCMCS streams, or flows. This system information may be embodied as a radio channel configuration, logical to physical channel mappings, neighbor list information, etc, for example.

[0005] A message referred to as a Broadcast Service Parameters Message (BSPM) carries this BCMCS-related signaling information. The size of the BSPM depends on factors such as the number of Broadcast-Multicast (BCMC) sessions for which logical-to-physical mappings (LPMs) have been established in the sector. An LPM specifies which BCMCS content is carried by what physical channel (such as a Forward Broadcast Supplemental Channel (F-BSCH) in cdma2000, for example) in the forward link. The BSPM may possibly be several hundreds of bytes long. The timely delivery of BSPM may require data rates on the order of several kbps.

[0006] A necessity exists to design and define efficient methods for carrying the BSPM that enable delivery of 'time-critical' BSPMs with low delays, so as to provide quick notification of availability of BCMC content for a BSPM flow and/or quick initiation of content delivery for a certain BCMC flow. In addition, the BSPM should use spectrally efficient channels for transmission and should not significantly impact battery life of BCMC-capable mobile stations. Further, the BSPM (and transmission thereof) should minimize impact on battery life of mobile stations that do not have BCMC capabilities.

[0007] Current techniques for transmission of the BSPM in third generation wireless communications networks such as cdma2000 3G.1x include use of a paging channel (PCH) and/or a Forward Common Control Channel/Forward Broadcast Control Channel (F-CCCH/F-BCCH). In third generation wireless communications networks such as cdma2000 3G.1x spread spectrum systems, a PCH is a code channel in a Forward CDMA Channel that is used for transmission of control information and pages from a base station to a mobile station. A paging channel slot

may be defined as an 80 ms interval on the PCH. Mobile stations operating in the slotted mode are assigned specific slots in which they monitor messages from the base station. Mobile stations in an idle state and operating in slotted mode only monitor selected slots on the PCH and F-CCCH, thereby improving battery life.

[0008] A feature known as 'Quick Paging' permits mobile stations to further conserve battery power beyond the savings achieved by slotted mode operation. A Quick Paging Channel (QPCH) is an un-coded, on-off-keyed (OOK) spread spectrum signal sent by base stations to inform slotted mode mobile stations, operating in the idle state, whether to monitor the PCH or the Forward Common Control Channel (F-CCCH). Like the PCH, the QPCH has an 80 ms duration. A paging indicator is a one-bit datum sent on the QPCH. Quick paging indicators are associated with mobile stations, in pairs, via a hashing algorithm. Appearance of both of its paging indicators in its assigned QPCH slot serves to alert a slotted mode mobile station, operating in the idle state, that the mobile should monitor the PCH or the F-CCCH starting in the next slot.

[0009] In general, the PCH technique involves paging to indicate BSPM changes, and paging to indicate what BSPMs are transmitted on the PCH. For BSPM transmission on the PCH, data rates are relatively low (up to only about 9.6 kbps). In addition, there exists low spectral efficiency, which is inefficient for transmitting long BSPMs in a timely manner.

[0010] Currently, PCH protocol provides two methods for the transmission of broadcast messages, (a) Multi-slot Broadcast Message Transmission; and (b) Periodic Broadcast Paging. Each method enables mobile stations operating in the slotted mode or in the non-slotted mode [define as compared to slotted mode] to receive broadcast messages. According to (a), a broadcast message is sent in a sufficient number of assigned slots such that it may be received by all mobile stations that are operating in the slotted mode. Thus, a BSPM transmission appears on all assigned slots in a slot cycle, which may result in an inefficient use of forward link resources.

[0011] According to (b), mobile stations configured to receive broadcast messages monitor a specific broadcast slot, such as the first slot of a broadcast paging cycle. If all of the broadcast messages to be transmitted fit within the first slot of a broadcast paging cycle, they may all be transmitted in this broadcast slot. If there is a single broadcast message to be transmitted, the single broadcast message may be transmitted at the beginning of this broadcast slot.

[0012] Alternately, one or more broadcast pages may be transmitted in the first slot of a broadcast paging cycle. Each broadcast page is associated with a subsequent broadcast slot. For each broadcast page, an associated broadcast message may be transmitted in the associated subsequent broadcast slot. A problem with (b) is that a non-BCMC capable mobile station that supports the QPCH will “wake up” to decode BSPM. This method thus may waste battery life of these non-BCMC capable mobile stations.

[0013] For transmitting a BSPM on a F-CCCH, paging on the F-CCCH is used to inform slotted mode mobiles of the BSPM transmission, and the F-BCCH is used to carry the BSPM. One method available for paging on the F-CCCH is use of a multi-slot enhanced broadcast page. However, this method has the same problem as the Multi-slot Broadcast Message Transmission for PCH. Namely, a BSPM transmission appears on all assigned slots in a slot cycle, which may result in inefficient use of forward link resources.

[0014] Another method for BSPM transmission on the F-CCCH includes use of a periodic enhanced broadcast page. However, this method has a problem similar to the Periodic Broadcast Paging described with respect to the PCH. In other words, the same battery life problem for mobile stations that do not support BCMCS exists. Additionally, there exists a minimum broadcast paging cycle of 5.12 seconds, which may adversely affect a delay requirement for delivery of “time-critical” BSPMs. Further, frequent changes in BSPM information technology may also require legacy mobile stations to monitor the F-BCCH, even though there have been no changes in other system information (unrelated to BCMCS).

SUMMARY OF THE INVENTION

[0015] Exemplary embodiments are directed to methods for signaling information to a group of users in a communication network supporting a broadcast-multicast service. One or more indicator bits of a sequence of indicator bits may be assigned to indicate transmission of signaling information that is related to the group. The sequence may then be transmitted to the group on a first channel, with the signaling information related to the group being transmitted on a second channel.

BRIEF DESCRIPTION OF THE DRAWINGS

[0016] Exemplary embodiments of the present invention will become more fully understood from the detailed description given herein below and the accompanying drawings, wherein like elements are represented by like reference numerals, which are given by way of illustration only and thus are not limitative of the exemplary embodiments of the present invention and wherein:

[0017] FIG. 1 is a diagram illustrating a slot structure of a quick paging channel in accordance with an exemplary embodiment of the invention.

[0018] FIG. 2 is a diagram illustrating a slot structure of a quick paging channel in accordance with another exemplary embodiment of the invention.

[0019] FIG. 3 is a diagram illustrating a slot structure of a quick paging channel and a BCMC slot of a paging channel or control channel in accordance with another exemplary embodiment of the invention.

[0020] FIG. 4 is a diagram illustrating a network connected to a group of users in which a slot structure of a quick paging channel in accordance with example embodiments may be implemented.

[0021] FIG. 5 is a diagram illustrating a method of signaling information to a group of users.

DETAILED DESCRIPTION OF THE EXEMPLARY EMBODIMENTS

~~[0020]~~**[0022]** Although the following description is described as based on a generic wireless communication network or system supporting Broadcast-Multicast services (BCMCS), and will be described in this exemplary context, it should be noted that the exemplary embodiments shown and described herein are meant to be illustrative only and not limiting in any way. As such, various modifications will be apparent to those skilled in the art for application to wireless communication systems or networks based on 3G-1x EV-DO, 3G-1x EV-DV and UMTS technologies that may currently support or be adapted to support BCMCS, for example, and are contemplated by the teachings herein.

~~[0021]~~**[0023]** Additionally where used below, the term 'user' may be considered synonymous to user equipment, subscriber, BCMCS subscriber, mobile station, remote station, access terminal, etc., and describes a remote user of wireless resources in a wireless communication network. A user may also be occasionally referred to as a receiver of a multicast message. Groups of users of BCMCS may be occasionally referred to as a 'BCMCS group' or 'multicast group' for purposes of brevity.

~~[0022]~~**[0024]** The terms base station and Node-B may be considered synonymous, and describe equipment that provides data connectivity between a network and one or more mobile stations. A system or network (such as an access network) may include one or more base stations.

~~[0023]~~**[0025]** Point-to-multipoint services such as BCMCS allow data from a single source entity to be transmitted to multiple endpoints. BCMCS is intended to efficiently use radio/network resources in transmitting data over a radio channel. Data may be transmitted to multicast areas as defined by the network. A network may selectively transmit BCMCS content on sectors within the multicast area which contain members of a multicast group.

~~[0024]~~**[0026]** A BCMCS received by a user may involve one or more successive multicast sessions. For example, a BCMCS might consist of a single on-going session (e.g. a multimedia stream) or may involve several intermittent BCMCS

sessions over an extended period of time (e.g. messages). Applications that may take advantage of BCMCS, and hence, of the exemplary embodiments of the present invention, may include, but are not limited to, voice dispatch or Press-To-Talk (PTT) type services, broadcast/multicast streaming, videoconferencing, corporate communications, distance learning, online bidding, online gaming and distribution of software, stock quotes, and news, etc.

[0025][0027] In general, the exemplary embodiments of the present invention are directed to signaling information to a group of users, and the reception of signaling information by a group of users, in a wireless communications network or system supporting broadcast-multicast services (BCMCS). For the following discussion, groups of users may be considered a 'BMC group', a 'multicast group' or simply referred to as a 'group' for reasons of brevity.

[0026][0028] An exemplary embodiment is directed to a signaling method for a group of users in a communication network supporting a broadcast-multicast service, in which a system overhead message, known as a 'Broadcast Service Parameters Message' (BSPM) is transmitted to each BMC group. The BSPM, which is carried in a paging channel or control channel, may be signaled to one or more users in the group by assigning one of more indicator bits arranged in one or more specified slots of a quick paging channel, for example. Alternatively, the quick paging channel may include indicators in given bit positions within a slot of the channel. The indicator may be mapped to signaling information to enable as a unique flow identification (BCMCS flow ID) for a given broadcast-multicast service content flow subscribed to by one or more users in the group.

[0027][0029] Another exemplary embodiment is directed to a method of signaling information to a group of users, in which a paging channel or common control channel may be transmitted to the group. The paging channel or common control channel (PCH/F-CCCH) may include a paging slot containing signaling information for a broadcast-multicast service subscribed to by one or more users of the group. The paging slot may be referred to as a broadcast-multicast (BMC) slot, for example.

~~[0028]~~~~[0030]~~ Another exemplary embodiment is directed to a method of signaling information to a group of users that combines the assigning of BSPM indicators in the QPCH with the use of the BCMC paging slot in the PCH/F-CCCH to carry the BCMCS-related signaling information. The QPCH is initially transmitted, and the PCH/F-CCCH with paging slot transmitted thereafter. The paging slot contains signaling information (such as the BSPM) for a broadcast-multicast service subscribed to by one or more of the users of the group.

~~[0029]~~~~[0031]~~ Another exemplary embodiment is directed to a method of signaling information to the group, in which signaling information is transmitted together with broadcast-multicast service content on a physical channel to one or more users of the group. In other words, a single physical channel, such as a F-BSCH, may be used to transmit the BSPM and the BCMCS content.

~~[0030]~~~~[0032]~~ Another exemplary embodiment is directed to a method of signaling information to the group, in which one part of the signaling information may be transmitted on a first channel, and another part of signaling information may be transmitted on a second channel, together with broadcast-multicast service content, to one or more users of the group. The first channel may be a QPCH and the second channel may be a F-BSCH, for example.

~~[0033]~~ FIG. 4 is a diagram illustrating a network 40 connected to a group of users 20. A slot structure of a quick paging channel according to example embodiments may be implemented in the network 40 connected to the group of users 20.

~~[0031]~~~~[0034]~~ FIG. 1 is a diagram illustrating a slot structure of a quick paging channel in accordance with an exemplary embodiment of the invention. Referring to FIG. 1, a slot structure of a quick paging channel (QPCH) 100 is illustrated, and the QPCH 100's relationship to a PCH/F-CCCH 150 carrying signaling information such as a BSPM in a broadcast slot 165.

~~[0032]~~~~[0035]~~ The BSPM may be transmitted continuously by each sector as an overhead message on the forward PCH or carried on the F-BCCH. A user (mobile station) should decode (read) the BSPM to obtain the relevant signaling information needed to receive BCMCS content over the traffic channel (F-BSCH). For example,

the BSPM may include data for each F-BSCH that carries BCMCS content. This data may include the radio channel configuration, data rate, frame size, channelization code data, multiplexing options and channel frequency of the F-BSCH. Additionally, for each BCMCS content, the BSPM may include data such as a BCMCS content identifier (e.g., BCMCS flow ID), BCMCS transmission indicator, and one or more logical-to-physical channel mappings (LPMs). For each LPM, neighbor BCMCS configuration and neighbor BCMCS parameters may be included. This may also be referred to as a 'neighbor list' for brevity.

~~[0033]~~~~[0036]~~ Referring again to FIG. 1, the QPCH 100 may include a plurality of QPCH slots 120, each slot duration being approximately 80 ms, although this slot size is not limited to 80 ms, other durations may be acceptable. An individual QPCH slot 120 may include quarter-slots 125. Each quarter slot 125 may carry an indicator bit; as shown in FIG. 1, these indicator bits are represented by pairs (A1, A2) and (B1, B2). These indicator bits may be referred to as 'BSPM Indicators'. In this case, these BSPM indicators are not specific to a particular BCMC group, but rather are indicators used by all BCMC groups. A wireless communication network may assign, on each QPCH 100, two indicator bit positions for all BCMCS flows on a QPCH slot 120. In other words, if a BCMCS flow 'A' represents "HBO" (network programming), for example, the two indicator bit positions for the 'A' BCMCS flow are A1 and A2.

~~[0034]~~~~[0037]~~ In FIG. 1, BSPM indicators (A1, A2) and (B1, B2) are carried on a QPCH slot 120 so as to precede a corresponding broadcast slot 165 of the PCH/F-CCCH 150. As shown in FIG. 1, the QPSK slot 120 is offset by about 100 ms from the broadcast slot 165 on the PCH/F-CCCH 150. In FIG. 1 the BSPM indicators are shown in the first bit positions in each quarter slot 125. The BSPM indicators may be set in existing indicator bit positions in the QPCH 100, in place of current reserve bit positions in the QPCH 100, or in bit positions to be newly defined for the QPCH 100.

~~[0035]~~~~[0038]~~ For example, referring to FIG. 5, In order to transmit signaling information to a group of users, such as a BCMC group, the network assigns the

BSPM indicator(s) to the QPCH channel 100 (S1), such as the given bit positions in quarter-slots 125 shown in FIG. 1, then transmits the QPCH 100 to the group (S2).

~~[0036]~~**[0039]** On the user side, and to receive BCMCS-related signaling information, the user should be BCMC-capable, operating in the slotted mode and supporting QPCH. The user should decode the QPCH slot 120, and hence read the indicators in the quarter-slots 125, to determine whether or not the user will monitor a subsequent broadcast slot 165 for a BSPM. If both BSPM indicators (A1, A2) and/or (B1, B2) are enabled (e.g., the user detects that both the BSPM indicators are 'ON'), then the user monitors the broadcast slot 165 immediately following the QPCH slot 120 for a BSPM. Otherwise, the user (mobile) does not monitor the broadcast slot 165 following the QPCH slot 120 for a BSPM, since at least one of the BSPM indicators is 'OFF' (not enabled).

~~[0037]~~**[0040]** The signaling methods described with respect to FIG. 1 may significantly improve battery life of mobile stations that do not support BCMCS, but support QPCH, while other users are not impacted at all. The structure in FIG. 1 also demonstrates efficient transmission of BSPM on the forward link, with no unnecessary repetition of BSPMs in a slot cycle.

~~[0038]~~**[0041]** BCMC-capable users that support QPCH have to monitor two additional bits in only one slot 120 of the QPCH 100 in a broadcast paging cycle. This is an insignificant impact on mobile station complexity, and has no adverse impact on BCMC-capable users that do not support QPCH. The user decodes the BSPM irrespective of whether the BSPM contains any information on a BCMC flow the user is interested in monitoring.

~~[0039]~~**[0042]** FIG. 2 is a diagram illustrating a slot structure of a quick paging channel in accordance with another exemplary embodiment of the invention. FIG. 2 is provided to illustrate a QPCH that has BSPM indicator positions for specified BCMC groups, rather than BSPM indicator positions for all BCMC groups in a sector or cell. FIG. 2 is similar to FIG. 1, thus only the differences are discussed.

~~[0040]~~**[0043]** In FIG. 2, the mobile station may employ a hashing procedure on the QPCH 100, in which signaling information such as BCMCS flow ID is used to "hash"

onto two indicator bit positions on the QPCH 100. The QPCH slot 120 of QPCH 100 is offset 100 ms from the broadcast slot 165 of the PCH/F-CCCH 150. The BSPM indicator bits may be set in existing indicator bit positions in the QPCH 100, in place of current reserve bit positions in the QPCH 100, or in bit positions to be newly defined for the QPCH 100.

[0041][0044] Unlike the exemplary embodiment in FIG. 1, the QPCH 100 of FIG. 2 has BSPM indicators A1 and A2 present in the first and third quarter-slots 125, but in different locations within each quarter-slot 125, as shown generally by arrows 124 and 126. Similarly, the QPCH 100 of FIG. 2 has BSPM indicators B1 and B2 present in the second and fourth quarter-slots 125, but in different locations within each quarter-slot 125, as shown generally by arrows 127 and 129. These BSPM indicators, as they depend on a flow parameter (BCMCS flow ID), thus are flow-specific indicators, unlike the embodiment of FIG. 1.

[0042][0045] FIG. 2 may be referred to for the following example. Consider a BCMC flow 'A' corresponding to HBO and BCMC flow 'B' corresponding to CNN. BSPM indicator positions 124 and 126 (A1, A2) correspond to HBO, and positions 127 and 129 (B1, B2) correspond to CNN. The BSPM indicator bits in these positions are carried on the QPSK slot 120 that precedes the broadcast slot 165. In this embodiment, since the BSPM indicators are flow specific, a mobile station (user) interested in CNN only monitors (B1, B2), and a user interested in both BCMCS contents (HBO, CNN) will monitor slot 120 for both pairs of indicators, (A1, A2) and (B1, B2). Although, here the HBO and CNN indicators here are shown in different quarter slot pairs, this need not be the case. For example, individual mobile stations may be required to monitor only one quarter slot pair within the slot in order to minimize complexity. In such a case, the indicators for HBO and CNN may need to be duplicated across quarter slot pairs.

[0043][0046] Thus, on the user side, to receive the signaling information, a user in a BCMC group decodes the QPCH 100 to read the BSPM indicators mapped to enable a unique flow identification for a given broadcast-multicast service content flow subscribed to by one or more users of the BCMC group. This is done so the

user can determine whether to monitor the PCH/F-CCCH 150 for the signaling information (BSPM), as described in the previous embodiment.

[0044][0047] In other words, a user (or more than one user) in a BCMC group should monitor (and decode) QPCH slot 120 for BSPM indicators corresponding to specified broadcast-multicast service content flows subscribed to by the user, i.e., the BSPM indicator corresponding to the BCMC flow ID. The user then will monitor the broadcast slot 165 that follows the QPCH slot 120 for a BSPM transmission, if the decoding of the QPCH slot 120 reveals that the two BSPM indicator bits are enabled ('ON') for at least one of the subscribed to broadcast-multicast service content flows. Otherwise, a BSPM indicator is considered not enabled ('OFF'), so the user skips monitoring of the broadcast slot 165 for the BSPM.

[0045][0048] The above embodiment may ensure that a mobile station will not decode the BSPM if the BSPM does not contain signaling information pertaining to any BCMC flow the mobile station is interested in, as evidenced by the BCMC flow ID to BSPM indicator hashing. Accordingly, the above signaling method may further conserve mobile battery life.

[0046][0049] FIG. 3 is a diagram illustrating a slot structure of a quick paging channel and a BCMC slot of a paging channel or control channel in accordance with another exemplary embodiment of the invention. Another exemplary embodiment is directed to a method of signaling information to a group of users, in which the PCH/F-CCCH to be transmitted to a BCMC group includes a paging slot. The paging slot, referred to as a 'BCMC slot' contains signaling information for a broadcast-multicast service subscribed to by one or more users of the group. The definition of this BCMC slot is similar to the broadcast slot that is specified on the PCH/F-CCCH.

[0047][0050] Referring now to FIG. 3, only differences from FIGS. 1 and 2 are described for reasons of brevity. FIG. 3 shows that a BCMC slot may be used in conjunction with the assigning of BSPM indicators as described in the exemplary embodiments of FIGS. 1 and/or 2. BSPMs are transmitted on a specific BCMC slot 365 of the PCH/F-CCCH 150. The BCMC slot 365 may be the first slot of a BCMC paging cycle. The BCMC paging cycle on the PCH/F-CCCH 150 may have a

duration satisfying the relation $B + N$, where $B = 2^i \cdot 16$, where i is a configuration parameter that is bounded by i_1 and i_2 , ($i_1 \leq i \leq i_2$). The parameter i may thus be a positive or negative integer. The parameter i can assume negative values, thereby providing shorter paging cycles for time critical applications. The constant N may be any positive integer ($N=0, 1, \dots, N-1$), so long as the BCMC paging cycle differs from the broadcast paging cycle. Different cycles for BSPM and broadcast paging minimizes the rate of collisions between the two. In addition, the impact on paging for unicast services may be more efficiently distributed across unicast mobiles. As discussed above, the parameter i could take on negative values, to allow for “negative BCMC paging cycles”. Accordingly, BCMC paging cycles smaller than current broadcast paging cycles in the standard are possible with the relation above.

[0048][0051] Somewhat similar to FIGS. 1 and 2, the BSPM indicators (as previously described) are carried in the QPCH slot 120 that is offset by 100 ms from the BCMC slot 365. The procedures for a BCMC-capable user that support QPCHs to receive signaling information are similar to that described above with respect to FIGS. 1 and 2, thus is not repeated in detail. For example, if the BSPM indicators are not flow-specific, and both BSPM indicators are enabled (‘ON’), then the mobile station monitors the BCMC slot 365 following the QPCH slot 120 for a BSPM. BCMC-capable mobiles not supporting QPCH 100 will monitor each BCMC slot 365 on PCH/F-CCCH 150 for BSPMs.

[0049][0052] Another exemplary embodiment is directed to a method of signaling information to the group, in which a single channel is used to transmit signaling information and BCMCS content. For example, BSPM transmission may be allowed on the F-BSCH, so that signaling data is transmitted together with broadcast-multicast service content on a single traffic channel to users of the BCMC group. For example, BSPM transmission on the F-BSCH may be allowed by the network reserving a specified field, such as SR_id 000, to indicate that a corresponding packet data unit (PDU) transmission is actually a BSPM. Accordingly, this exemplary embodiment may be suitable for transmission of BSPMs to mobile stations monitoring a BCMC flow but not any common channels (F-CCCHs/BCCHs)

to provide what may be a spectrally efficient method of transmitting large BSPMs to such mobile stations.

~~[0050]~~**[0053]** Another exemplary embodiment is directed to a method of signaling information to the group, in which one part of the signaling information is transmitted on a first channel, and another part of signaling information is transmitted on a second channel, together with broadcast-multicast service content, to one or more users of the group. The first channel may be the QPCH and the second channel may be the F-BSCH, for example.

~~[0051]~~**[0054]** For example, only part of the BSPM data needs to be transmitted for the BCMC group to determine whether or not to monitor for a BSPM. This part data could include broadcast-multicast service content identifier (BCMC flow ID) and/or logical to physical channel mapping data (LMP) may be transmitted on the QPCH 100, or alternatively on the PCH/F-CCCH 150. The remaining BSPM data could be transmitted on a traffic channel with the BCMCS content, such as on the F-BSCH.

~~[0052]~~**[0055]** The exemplary embodiments of the present invention may offer several advantages. Paging may be used to indicate BSPM transmission by assigning BSPM indicators for BCMCS on the QPCH. Optionally, BCMC paging slots may be defined on the PCH and F-CCCH. An F-CCCH may be optionally used for BSPM transmission, in addition to use of the PCH. This may enable higher data rates up to 38.4 kbps, not previously possible on the F-CCCH. In addition, BSPM transmission in accordance with the exemplary embodiments may demonstrate improved spectral efficiency and may be suitable for transmitting BSPMs in a timely and efficient manner.

~~[0053]~~**[0056]** Moreover, BSPM transmission using traffic channels such as the F-BSCH, in addition to common control channels, may provide additional availability and options to the network operator. Further, the signaling methods are designed so as to minimally impact battery life of mobile stations that do not support BCMCS, while efficiently using forward link resources for transmission of BSPMs. Accordingly, "time-critical" BSPMs may be transmitted to users in a timely manner,

and the aforementioned methods may allow BSPMs to be transmitted to users monitoring a BCMC flow, but not monitoring any common channel.

~~[0054]~~[0057] Further, the exemplary embodiments of the present invention may allow BSPM updates to be directed to specific BCMC groups that are intended recipients of the updates, without requiring BSPM messages to be frequently repeated in their entirety. If periodic transmission of BSPM in its entirety (similar to the current method of BSPM transmission and/or periodic broadcast paging) is enabled, perhaps with a BCMC-specific sequence indicator akin to CONFIG_MSG_SEQ to conserve the battery life of non-BCMC capable mobile stations, then the methods described herein could be employed to provide time critical BSPM updates in a spectrally efficient and battery life conserving manner. The updates may include merely differential changes (e.g. new BCMC flow ID, neighbor list change) in the BSPM message, and not the entire BSPM.

~~[0055]~~[0058] The exemplary embodiments of the present invention being thus described, it will be obvious that the same may be varied in many ways. Such variations are not to be regarded as departure from the spirit and scope of the exemplary embodiments of the present invention, and all such modifications as would be obvious to one skilled in the art are intended to be included within the scope of the following claims.

What is claimed is:

1. A method of signaling information to a group of users. comprising:
 assigning at least one indicator bit of a sequence of indicator bits to indicate a transmission of signaling information related to broadcast-multicast service that is related to the group; and
 transmitting the sequence to the group and the signaling information related to the group.
2. The method of claim 1, wherein the sequence is transmitted on a first channel and the broadcast-multicast service related signaling information is transmitted on a second channel.
3. The method of claim 2, wherein
 the first channel is a quick paging channel that is slotted and sub-divided into quarter slots; and
 the assigning step includes assigning one or more indicator bits to specified quarter-slots of the quick paging channel.
4. The method of claim 1, wherein
 the indicator bit is a Broadcast Service Parameters Message (BSPM)
indicator informing at least one group of a BSPM transmission,
 the group is a broadcast-multicast (BCMC) group, and
 the BSPM includes signaling information intended for one or more BCMC groups.
5. The method of claim 2, wherein the assigning step includes assigning at least one indicator for broadcast-multicast service content flows on a slot of the first channel, the slot being 100 ms offset from a specified slot on the second channel.

6. The method of claim 5, wherein
the first channel is one of a paging channel and a common control channel, and
the specified slot is a broadcast slot of the second channel.
7. The method of claim 5, wherein the specified slot is a given broadcast-multicast slot of the second channel.
8. A method of receiving signaling information in a communication network supporting a broadcast-multicast service, comprising:
decoding a first channel containing at least one indicator related to signaling information for a broadcast-multicast service to determine whether to monitor a second channel for the signaling information.
9. The method of claim 8, wherein
the first channel is a quick paging channel,
the second channel is one of a paging channel and a common control channel,
the at least one indicator is a Broadcast Service Parameters Message (BSPM) indicator informing one or more groups of users of a BSPM transmission to the groups, the BSPM transmission containing signaling information for a broadcast-multicast service.
10. The method of claim 8, further comprising:
monitoring a slot on the second channel that follows the quick paging channel slot for a BSPM transmission, if the decoding step determines that the BSPM indicator(s) are enabled, else skipping the monitoring step if at least one of the BSPM indicator(s) is not enabled.
11. The method of claim 10, wherein the slot on the second channel is one of a broadcast slot and a broadcast-multicast (BCMC) slot.

12. A method of signaling a group of users in a communication network supporting a broadcast-multicast service, comprising:

transmitting a channel containing signaling information to the group, the channel including at least one indicator in a given position of a slot of the channel, the indicator mapped to signaling information for enabling unique flow identification of a given broadcast-multicast service content flow subscribed to by one or more users in the group.

13. The method of claim 12, wherein

the channel is a quick paging channel, a slot of the quick paging channel further comprised of four quarter slots, at least one indicator per quarter slot, and the at least one indicator is a Broadcast Service Parameters Message (BSPM) indicator informing one or more groups of a BSPM transmission to the groups, the BSPM transmission containing signaling information for a broadcast-multicast service.

14. The method of claim 13, further comprising

determining which BSPM indicator is related to the group using a mobile hashing procedure based on an identification number.

15. A method of receiving signaling information at a group of users in a communication network supporting a broadcast-multicast service, comprising:

decoding a first channel containing at least one indicator mapped to signaling information for enabling unique flow identification for a given broadcast-multicast service content flow subscribed to by one or more users of the group, to determine whether to monitor a second channel for the signaling information.

16. The method of claim 15, wherein

the first channel is a quick paging channel,

the second channel is one of a paging channel and a common control channel,

the at least one indicator is a Broadcast Service Parameters Message (BSPM) indicator informing the group of a BSPM transmission to the group, the BSPM transmission containing signaling information for a broadcast-multicast service.

17. The method of claim 16, further comprising, for one or more users of a group:

first monitoring a slot of the quick paging channel for BSPM indicators corresponding to one or more broadcast-multicast service content flows subscribed to by one or more users of the group; and

second monitoring a slot of the send channel that follows the quick paging channel slot for a BSPM transmission, if the decoding step determines that the two BSPM indicators are enabled for at least one of the subscribed to broadcast-multicast service content flows, else skipping the second monitoring step if at least one of the BSPM indicator(s) is not enabled.

18. The method of claim 17, wherein the slot on the second channel is one of a broadcast slot and a broadcast-multicast (BCMC) slot.

19. A method of signaling a group of users in a communication network supporting a broadcast-multicast service, comprising:

transmitting a channel to the group, the channel including a paging slot containing signaling information for a broadcast-multicast service subscribed to by one or more users of the group.

20. The method of claim 19, wherein the channel is a paging channel or a common control channel.

21. The method of claim 19, wherein the transmitting step includes transmitting a Broadcast Service Parameters Message (BSPM) containing signaling information for a broadcast-multicast service to one or more users of the group on a given broadcast-multicast (BCMC) slot of the channel.

22. The method of claim 21, wherein
the BCMC slot is a first slot of a BCMC paging cycle on the channel, and
the BCMC paging cycle is different in duration than a broadcast paging cycle of a broadcast slot on the channel.

23. The method of claim 22, wherein the BCMC paging cycle has a duration of $B + N$, where N is a positive integer ($N=0, 1, \dots, N-1$) and B is defined by $B=2^{i*}16$, where i is a configuration parameter bounded by i_1 and i_2 , ($i_1 \leq i \leq i_2$), and where i_1 and i_2 are adapted to assume a positive integer or negative integer value.

24. A method of signaling information to a group of users in a communication network supporting a broadcast-multicast service, comprising:
assigning at least one indicator related to signaling information for a broadcast-multicast service on a first channel;
transmitting the first channel to the group; and
transmitting a second channel including a slot containing the signaling information for a broadcast-multicast service subscribed to by one or more users of the group.

25. The method of claim 24, wherein the slot on the second channel is one of a broadcast slot and a broadcast-multicast (BCMC) slot.

26. The method of claim 24, wherein
the first channel is a quick paging channel,
the second channel is one of a paging channel and a control channel,

the indicator is a Broadcast Service Parameters Message (BSPM) indicator informing the group of a BSPM in a given slot of the second channel, the BSPM containing signaling information for a broadcast-multicast service to one or more users of the group.

27. The method of claim 26, wherein the assigning step includes assigning two BSPM indicators for broadcast-multicast service content flows on a slot of the first channel, the slot being 100 ms offset from a slot on the second channel that contains the broadcast-multicast service content.

28. A method of signaling information to a group of users in a communication network supporting a broadcast-multicast service, comprising:
transmitting signaling information together with broadcast-multicast service content on a traffic channel to one or more users of the group.

29. A method of signaling information to a group of users in a communication network supporting a broadcast-multicast service, comprising:
first transmitting one part of signaling information on a first channel,
second transmitting another part of the signaling information on a second channel carrying broadcast-multicast service content to one or more users of the group.

30. The method of claim 29, wherein the first transmitting step includes transmitting at least one of a broadcast-multicast service content identifier and logical to physical channel mapping data on one of a paging channel and control channel.

31. The method of claim 29, wherein the second transmitting step includes transmitting at least one of radio channel configuration, neighbor list data for broadcast-multicast service content, data rate, frame size, channelization code data

and multiplexing options together with broadcast-multicast service content on a broadcast supplemental channel to one or more users of the group.

METHODS FOR SIGNALING BROADCAST AND MULTICAST INFORMATION IN COMMUNICATION NETWORKS

ABSTRACT OF THE DISCLOSURE

Methods for signaling information to a group of users in a communication network supporting a broadcast-multicast service are described, in which one or more indicator bits of a sequence may be assigned to indicate transmission of signaling information that is related to the group. The sequence may be transmitted to the group on a first channel, with the signaling information related to the group being transmitted on a second channel.